

Company	Name	Tech.	Power / W	Socket	EAN	Eaton Profile ID	max nr. of LED's by Peak or RMS Current 250W DA	Maximum nominal LED Power / W 250W DA	Dimming profile				Time / Periods	WUT / STUP	Best Standard Profile (1st=OK, 2nd Average OK)	Comment
									Dim Type	MIN	MID	MAX				
Eglo	LED G9 2,5W	LED ND	2,5	G9	9002759114619	0,6	n.a.	n.a.	Switch	100	100	100	0	0	ON/OFF only	
Eglo	Eglo LED Spot GU10 38° 6W 390 lm dimmbar	LED	6,0	GU10	9002759114534	42,2	11	66	Auto-TE	20	45	70	0	0	LED 2	
Eglo	LED Globelampe 3000K matt 600lm dimmbar	LED	9,0	E27	9002759111861	42,1	4	36	Auto-TE	24	45	75	0	0	LED 1	
ESTO Lighting	LED Lamp A60	LED ND	5,0	E27	9003348106428	0,6	n.a.	n.a.	Switch	100	100	100	0	0	ON/OFF only	
ESTO Lighting	LED Filament Candle 2W	LED ND	2,0	E14	9003348117264	0,6	n.a.	n.a.	Switch	100	100	100	0	0	ON/OFF only	
ESTO Lighting	LED G9 1,5W 3000K	LED ND	1,5	G9	9003348102895	0,6	n.a.	n.a.	Switch	100	100	100	0	0	ON/OFF only	
ESTO Lighting	LED Spot 3W GU10	LED ND	3,0	GU10	9003348872590	0,6	n.a.	n.a.	Switch	100	100	100	0	0	ON/OFF only	
GE	Dimmable LED 8w GLS E27 lamp 2700K 470lm	LED	8,0	E27	0043168987837	36,2	17	136	Auto-TE	8	25	65	0	0	LED 4, LED 3	
GE	LED Spot Energy Smart	LED	5,0	GU10	43168984492	36,3	20	100	Auto-TE	24	45	70	0	0	LED 1	
GE	LED bulb dimmable lamp 4W P45 E27 240V	LED	4,0	E27	0043168973106	36,1	8	32	Auto-TE	25	45	65	0	0	LED 1	
Globo	LED Kerze E14 3W	LED ND	3,0	E14	9007371224708	0,6	n.a.	n.a.	Switch	100	100	100	0	0	ON/OFF only	
Globo	LED G9 1,9W 3000K	LED ND	1,9	G9	9007371250806	0,6	n.a.	n.a.	Switch	100	100	100	0	0	ON/OFF only	
Havells-Sylvania	TOLEDO+ AGL A60 DIM	LED	12,0	E27	5410288264288	45,3	13	156	Auto-TE	23	36	70	0	0	LED 1	Good dimmable
Havells-Sylvania	REFLED+ ES50 34SLM	LED	6,5	GU10	5410288267906	45,4	8	52	Auto-TE	20	45	75	0	0	LED 2	
Havells-Sylvania	ToLEDo Candle Dim Frosted 250LM E14 SL	LED	4,5	E14	5410288269252	45,1	10	45	Auto-TE	25	45	75	0	0	LED 1	
Havells-Sylvania	TOLEDO 470LM DIM	LED	6,5	E14	5410288269450	45,2	6	39	Auto-TE	25	40	70	0	0	LED 1	
Homeware	LED-Leuchtmittel Kerze 4W E14	LED ND	4,0	E14	9008420107881	0,6	n.a.	n.a.	Switch	100	100	100	0	0	ON/OFF only	
Ikea / LEDARE	LED-Lampe	LED ND	8,0	GU10	8025590722379	0,6	16	128	Switch	100	100	100	0	0	ON/OFF only	
Ikea / LEDARE	LED-Lampe	LED	16,5	E27	202.492.26	31,2	5	82,5	Auto-TE	10	30	70	0	0	LED 4, R/L/C Standard	Good dimmable
Ikea / LEDARE	LED-Lampe	LED	10,0	E27	602.553.62	31,3	7	70	Auto-TE	12	34	75	0	0	LED 4, R/L/C Standard	
Ikea / LEDARE	LED-Lampe	LED	13,0	E27	002.574.82	31,1	5	65	Auto-TE	13	30	75	0	0	LED 4, R/L/C Standard	
Jedi Lighting	JEDI Lighting 230 V E27 7.5 W	LED FB	7,5	E27	JED01249	0,6	n.a.	n.a.	Switch	100	100	100	0	0	ON/OFF only	
Ledon	LED-Lampe A65	LED	10,0	E27	9009453001511	35,1	16	160	Auto-TE	12	28	60	0	0	LED 3	quick flash when starting but then good
Ledon	LED-Tropfen P45	LED	5,0	E14	9120044927925	35,3	14	70	Auto-TE	25	40	70	0	0	LED 1	
Ledon	LED-Lampe A60	LED	10,0	E27	9009453003560	35,2	5	50	Auto-TE	25	45	75	0	0	LED 1	Good
Ledon	LED-Spot MR16	LED	5,0	GU10	9009453002372	35,4	8	40	Auto-TE	20	40	75	0	0	LED 2	
LG	LED-Lampe	LED	12,8	E27	8808992455912	34,1	5	64	Auto-TE	20	45	75	0	0	LED 2	
Livarno	LED-Lampe mit Bewegungssensor	LED ND BM	6,0	E27		0,6	n.a.	n.a.	Switch	100	100	100	0	0	ON/OFF only	
Megaman	Megaman 230 V GU9 2 W	LED	2,0	GU9	4020856491223	0,6	n.a.	n.a.	Switch	100	100	100	0	0	ON/OFF only	
Megaman	Megaman 230 V E14 3 W	LED ND	3,0	E14	4020856210503	0,6	n.a.	n.a.	Switch	100	100	100	0	0	ON/OFF only	
Megaman	LED Lampe	LED	11,0	E27	4020856000159	32,1	16	176	Auto-TE	18	30	55	0	0	LED 3	
Megaman	LED Lampe	LED	4,0	E14	4020856210282	32,3	40	160	Auto-TE	20	28	40	0	0	LED 5, LED 1	
Megaman	ESL GSU111d	ESL	11,0	E27	MM46012	32,4	10	110	Auto-TE	30	45	65	0	3	ESL/CFL	
Megaman	ESL CL809d	ESL	9,0	E14	MM46602	32,2	8	72	Auto-TE	30	45	65	0	3	ESL/CFL	
Müller Licht	LED Leuchtmittel E27 EB1400362	LED ND	3,0	E27	20016630	0,6	n.a.	n.a.	Switch	100	100	100	0	0	ON/OFF only	
Müller Licht	LED Blub 3W E14	LED ND	3,0	E14	4018412029973	0,6	n.a.	n.a.	Switch	100	100	100	0	0	ON/OFF only	
Müller Licht	LED Leuchtmittel E27 EB1400369	LED	7,0	E27	20016647 / 25895	48,1	25	175	Auto-TE	20	40	80	0	0	LED 2	Good dimmable
Müller Licht	LED Leuchtmittel E14 EB1400369	LED	5,5	E14	25898	48,2	8	44	Auto-TE	25	45	70	0	0	LED 1	
Müller Licht	LED Leuchtmittel E10 EB1400378	LED	4,0	GU10	20017392 / 23822	48,3	7	28	Auto-TE	22	40	65	0	0	LED 1	
MX-Logistika SL	LED Candle 3W E14	LED ND	3,0	E14	9009852000115	0,6	n.a.	n.a.	Switch	100	100	100	0	0	ON/OFF only	
Nextec	Premium 738	LED	6,8	GU10	5908293907738	51,1	20	136	Auto-TE	23	33	45	0	0	LED 5, LED 3	
Nice Price	LED 230V (nicht dimmbar)	LED ND	4,0	GU10	4000870033937	0,6	5	20	Switch	100	100	100	0	0	ON/OFF only	
OK	Energiesparlampe (nicht dimmbar)	ESL ND	20,0	E27	ET-2-20W-E27	0,6	6	120	Switch	100	100	100	0	0	ON/OFF only	
Osram	LED SUPERSTAR CLASSIC B advanced	LED	6,0	E14	4052899911413	44,5	23	138	Auto-TE	18	28	45	0	0	LED 3	no smooth start - then OK
Osram	LED SUPERSTAR CLASSIC P advanced	LED	3,8	E27	4008321992352	44,1	36	136,8	Auto-TE	12	28	45	0	0	LED 3	no smooth start - then OK
Osram	LED SUPERSTAR CLASSIC A advanced	LED	13,5	E27	4052899914384	44,3	10	135	Auto-TE	18	40	70	0	0	LED 4, R/L/C Standard	Slow reaction
Osram	LED SUPERSTAR CLASSIC P advanced	LED	6,0	E27	4052899911475	44,7	22	132	Auto-TE	16	28	40	0	0	LED 3	no smooth start - then OK
Osram	LED SUPERSTAR CLASSIC A advanced	LED	6,0	E27	4052899911161	44,4	20	120	Auto-TE	26	46	70	0	0	LED 1	
Osram	Leuchtstofflampe DIM	ESL	15,0	E27	DINT DIM GL 15W/825	44,8	8	120	Auto-TE	38	55	80	0	3	ESL/CFL	
Osram	LED SUPERSTAR CLASSIC B	LED	4,0	E14	4008321994035	44,2	12	48	Auto-TE	12	30	70	0	0	LED 4, R/L/C Standard	
Osram	LED SUPERSTAR PAR16 advanced	LED	3,0	GU10	4008321881816	44,6	8	24	Auto-TE	20	40	70	0	0	LED 2	
Paulmann	LED 230V	LED	11,0	E27	400087028142000	43,1	6	66	Auto-TE	25	45	70	0	0	LED 1	
Paulmann	LED 230V	LED	4,0	GU10	400087028144400	43,2	8	32	Auto-TE	24	40	70	0	0	LED 1	
Philips	Corepro LED Bulb	LED	10,0	E27	871829174741300	41,6	12	120	Auto-TE	20	34	75	0	0	LED 2	
Philips	CorePro LED Luster	LED	6,0	E14	871829176240900	41,11	20	120	Auto-TE	20	36	75	0	0	LED 2	
Philips	MASTER LED BULB Dimtone	LED	8,0	E27	871829119200800	41,5	12	96	Auto-TE	25	40	60	0	0	LED 1	no smooth start - then OK
Philips	MASTER LED Spot	LED	4,3	GU10	871869645709200	41,18	40	172	Auto-TE	10	40	70	1	20	R/L/C Standard, LED2	
Philips	LED Spot	LED	4,2	GU10	871829119286200	41,14	40	168	Auto-TE	12	24	40	0	0	LED 3	
Philips	LED Candle	LED	4,0	E14	871829167078000	41,12	40	160	Auto-TE	16	34	55	0	0	LED 3	Good dimmable
Philips	Tornado ESL	ESL	15,0	E27	872790092040400	41,17	10	150	Auto-TE	25	38	65	0	0	LED 1	
Philips	LED Spot	LED	4,0	E14	871829119292300	41,9	30	120	Auto-TE	17	28	40	0	0	LED 3	
Philips	Tornado ESL	ESL	20,0	E27	871016339470110	41,13	6	120	Auto-TE	25	38	65	0	0	LED 1	
Philips	Softone ESL	ESL	20,0	E27	872790082523700	41,16	6	120	Auto-TE	25	38	60	0	10	ESL/CFL	
Philips	LED Lampe	LED	6,0	E27	871829176246100	41,3	18	108	Auto-TE	24	36	60	0	0	LED 1	
Philips	Master LED Luster	LED	3,5	E14	871829174325500	41,8	28	98	Auto-TE	8	26	45	0	0	LED 3	Good dimmable
Philips	MASTER LED Luster	LED	6,0	E27	871829174188600	41,2	16	96	Auto-TE	22	31	55	0	0	LED 5, LED 1	Good dimmable
Philips	Softone ESL	ESL	12,0	E27	872790082518300	41,15	8	96	Auto-TE	25	33	50	0	1	ESL/CFL	
Philips	MASTER LED Candle	LED	3,5	E14	871829174321700	41,10	26	91	Auto-TE	12	30	45	0	0	LED 3	Good dimmable
Philips	MASTER LED BULB	LED	18,0	E27	871829175856300	41,7	4	72	Auto-TE	14	40	70	0	0	LED 4, R/L/C Standard	
Philips	Master LED Bulb	LED	7,0	E27	871829167196100	41,4	4	42	Auto-TE	20	45	65	0	0	LED 1	
Philips	MASTER LED Spot	LED	8,0	GU10	871829168233200	41,1	4	32	Auto-TE	26	44	70	0	0	LED 1	

Status: 10.11.2015

Profile Name	Category ID	Profile ID	Dim-Type	MIN	MID	MAX	Warmup / s	0%	10%	20%	30%	40%	50%	60%	70%	80%	90%	100%
R/L/C Standard (15 - 48 - 80 Auto)	0	1	Auto	15	48	80	0	15	22	28	35	41	48	54	61	67	74	80
LED 1 (26 - 43 - 68 Auto)	0	2	Auto	26	43	68	0	26	29	32	35	39	43	47	52	57	62	68
LED 2 (20 - 40 - 75 Auto)	0	3	Auto	20	40	75	0	20	23	26	30	35	40	46	52	59	67	75
LED 3 (15 - 30 - 45 Auto)	0	4	Auto	15	30	45	0	15	18	21	24	27	30	33	36	39	42	45
CFL/ESL (35 - 50 - 70 Auto 3s)	0	5	Auto	35	50	70	3	35	38	40	44	47	50	54	58	62	66	70
ON/OFF only	0	6	Switch	100	100	100	0	100	100	100	100	100	100	100	100	100	100	100
LED 4 (15 - 35 - 70 Auto)	0	7	Auto	15	35	70	0	15	18	21	25	30	35	41	47	54	62	70
LED 5 (20 - 30 - 50 Auto)	0	8	Auto	20	30	50	0	20	21	23	25	27	30	33	37	41	45	50
LED 6 (30 - 37 - 50 Auto)	0	9	Auto	30	37	50	0	30	31	32	33	35	37	39	42	44	47	50
LED 7 (25 - 40 - 70 Leading Edge)	0	10	Leading Edge	25	40	70	0	25	27	29	32	36	40	45	50	56	63	70